

# RADION smoke

www.boschsecurity.com



**BOSCH**

Invented for life



- ▶ Externally visible LED that indicates smoke detector status
- ▶ A built-in sounder for alarm alerts
- ▶ Supervised for low-battery, tamper, and removal from mounting surface tamper conditions
- ▶ Operational up to 5 years using two user replaceable CR123A Lithium batteries

RADION wireless from Bosch provides the range, scalability and exceptional battery life required to ensure reliable performance and superior quality. Advanced diagnostics and multiple device enrollment options make installation and maintenance simple and cost effective. With a complete line of peripherals, RADION provides the flexibility for virtually any application requirement.

## System overview

RADION smoke is a photoelectric (RFSM-A version also includes “dual fixed/rate-of-rise on” functionality) wireless detector that transmits alarm signals to the wireless receiver when smoke is detected.

## Functions

### Alarm Mode

The detector’s built-in 85 dBA sounder initiates an alarm signal and an RF signal indicating the alarm condition is sent when the detector goes into alarm mode. The receiver signals the control panel identifying the specific detector in alarm. Alarm conditions are non-latching so if the alarm condition goes away (smoke dissipates), the detector returns to a normal state.

The photoelectric smoke detector continuously acquires ambient obscuration data as it monitors the surrounding environment. The red LED blinks every time a sample is taken. If any one sample is above the calibrated alarm threshold, two more samples are taken at 4 second intervals. If all three samples are above the calibrated alarm threshold, the detector goes into alarm mode.

### Status indicator

The LED and sounder indicate the status of the detector but not of the RF signaling circuitry. Under normal conditions, the red LED flashes regularly while the sensor monitors the surrounding environment. When the sensor detects smoke, the LED changes from flashing to steady ON and the sounder produces a loud, continuous tone.

### Test Silence button operation

A Test Silence button allows for performance of the sounder and sensitivity tests and silencing of alarm sounder and trouble chirp.

### Drift compensation

The detector has built-in drift compensation that allows the alarm to adjust sensitivity automatically as it becomes dirty over time. The drift compensation feature dramatically increases the time between cleanings, as well as reducing the chance of a nuisance alarm.

## Certifications and approvals

Region	Certificate	
US	UL 268 Smoke Detectors for Fire Alarm Systems	
Region	Certification	
Europe	CPR	1134-CPR-039 [optical smoke alarm device component]
	CE	2004/108/EC EMC Directive (EMC); 2006/95/EC Low-Voltage Directive (LVD); 1999/5/EC Radio equipment and Telecommunications Terminal Equipment (R&TTE); 2011/65/EU Restriction of the use of certain hazardous substances in electrical and electronic equipment
USA	UL	20121214-S3019
	UL	UL 268 - Smoke Detectors for Fire Alarm Signaling Systems
	CSFM	California State Fire Marshal (see our website)
	FCC	Part 15 Security/Remote Control Transmitter 433.42 MHz [433.42 MHz]
Canada	IC	1249A-RWSSFT [-A model numbers]
Brazil	ANATEL	0770-14-1855

## Installation/configuration notes

### Mounting considerations

Mount smoke detectors on interior ceilings preferably at, or near the center of the ceiling. When mounting in the center of the ceiling is not practical, mount on the ceiling no closer than 10 cm (4 in) to walls or corners, or on an inside wall between 10 cm (4 in) and 15 cm (6 in) from the ceiling, near the middle of the wall.



### Notice

Do not mount smoke detectors on drop ceiling tiles. Mount to a metal runner. Because installation on metal surfaces can affect the RF propagation pattern of the radio transceiver, verify the suitability of the installation site before detector installation.

## Parts included

Quantity	Component
1	Smoke detector
2	Lithium battery (CR123A)
1	Dust cover
1	Hardware pack
1	Literature pack

## Technical specifications

### Properties

Dimensions	142 mm x 61 mm (5.6 in x 2.4 in)
------------	----------------------------------

### Power

Power/Voltage	Two CR123A Lithium battery, 3 VDC
Battery life	Up to 5 years

### Environmental considerations

Sensitivity	0.14 +/- 0.04 bM/m (0.5%/ft - RFSM-A only)
Temperature	0°C to +49°C (+32°F to +120°F)
Relative humidity	Up to 93% non-condensing
Cover and wall tamper switch	Transmits a tamper switch signal when the unit is removed from its base, or the unit is pulled away from the mounting surface.
Drift compensation adjustment	-1.64%/m (0.5%/ft) maximum
Sounder	85 dBA at 3 m
Frequency	433.42 MHz
Use	Intended for indoor use

### Heat alarm specifications (applies to RFSM-A only)

Rate of rise:	15°F (8.3°C/min >40.6°C)
Fixed	135°F +/- 5°F (57.2°C +/- 2.8°C)

### Compatibility

Receivers:	B810 wireless receiver (compatible with RFSM-A only)
------------	--

## Ordering information

### RFSM-A (433.42 MHz)

Photoelectric and dual fixed/rate-of-rise detector. For use in North and South America.

Order number **RFSM-A**

### RFSM (433.42 MHz)

Photoelectric detector. For use in Europe, Africa, and Australia.

Order number **RFSM**

### RFSM-CHI (433.42 MHz)

Photoelectric detector. For use in China only.

Order number **RFSM-CHI**

**Represented by:**

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
emea.securitysystems@bosch.com  
emea.boschsecurity.com

**Germany:**  
Bosch Sicherheitssysteme GmbH  
Robert-Bosch-Ring 5  
85630 Grasbrunn  
Germany  
www.boschsecurity.com

**North America:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
onlinehelp@us.bosch.com  
www.boschsecurity.us

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia